

WIZORD 4I ENERGIZER



The Wizord energizers have been field tested for many years and boast unsurpassed reliability. Simple to install and easy to maintain.

Features:

- 3.7 Joule output energy (single zone)
- Robust and flexible design for home and commercial security
- Built-in alarm monitors tampering or faults on the high voltage and earth fence wires
- Connectable to armed response radio or GSM module
- Lightning and power surge protection
- Intelligent power saving to extend battery life
- Easy-to-use tag included for controlling the energizer
- Powered by 240V mains and includes built-in battery for back-up power
- Built-in gate alarm input to monitor if the gate is open or closed

Specifications:

Enclosure size	285(L) x 212(W) x 120(D)mm
Weight	3.1kg excluding battery (7AH) 5.3kg including battery (7AH)
IP rating	IPx4
Operating temperature	-10°C to 50°C
Operating humidity	< 80% non-condensing
Electrical supply voltage	240V
Typical power consumption	18VA (normal operating conditions)
Standby Time	24hrs (fully charged battery)
Energy output	3.7 Joule per zone (500 Ohms load)
Open circuit voltage	8000V

Stock Code	Description
E-WIZ4I	Wizord 4i Energizer